



## RADIO TRANSCEIVER 849

### SPECIFICATIONS:

#### COMMUNICATION

Radio frequency:

- 868 MHz 2-way

- 433 MHz 1-Way

Range 100 meters

#### OPERATION

1 x Joystick (2-axis)

8 x Function buttons

8 x Programmable display indications

6 x Operation modes via the menu

(a total of 48 functions)

#### OTHER

Battery: 3 x AAA-batteries

Built-in quick charger 10-30V

Operational time ~8H

Internal antenna

Optional: wireless charging

Optional: magnetic

Optional: Belt Clip

Stop function 13849-1 PL-d CAT3

IP-class: IP65

Dimensions: 165 x 77 x 52 mm

Weight: ~300g with battery

The CanCom family are modules and radio transmitters for smart control of mobile hydraulics. Now we are launching a new robust radio transmitter with many smart features.

The radio transceiver has 8 buttons but also a joystick for proportional control in 2 axis. The joystick can be used in combination with buttons to control your machine proportionally. The radio transceiver can also have programmable feedback indications displayed. This can show the status of sensor and alarm.

In order to use the hand transceiver fully, you can quickly switch between 6 different menu pages, and then let your buttons have a different functions on each page. For example: page 1 can control the machine functions, page 2 control the support legs, and page 3 the lights, and so on.

The transceiver is operated by 3xAAA batteries and has a built-in rapid charger 10-30V. Wireless charging is available as an option.

Together with CanCom Multi-module 60, a safety system of the ISO EN 13840-1 PL d CAT3 obtained for the stop function.

**PL-d  
Compliant**

